

	Symbol	Unit	Measuring Conditions			Wide Band Filter Material
			Freq.	Flux den.	Temp.	A102
Initial Permeability	μ_i		$\leq 10\text{kHz}$	0.25mT	25°C	10000 $\pm$ 30%
Relative Loss Factor	$\tan\delta/\mu_i$	10^{-6}	10kHz	< 0.25mT	25°C	< 10
			100kHz		25°C	< 60
Saturation Flux Density	Bs	mT	10kHz	H = 1200A/m	25°C	380
					100°C	180
Remanence	Br	mT	10kHz	H = 1200A/m	25°C	95
					100°C	75
Temperature Factor of Permeability	α_μ	$10^{-6}/^\circ\text{C}$	10kHz	< 0.25 mT	0 ~ 20°C	-1 ~ 1
					20 ~ 70°C	-1 ~ 1
Hysteresis Material Constant	η_B	$10^{-6}/\text{mT}$	10kHz	1.5-3.0mT	25°C	< 1
Disaccommodation Factor	D_F	10^{-6}	10kHz	< 0.25 mT	25°C	< 2
Curie Temperature	T_c	°C				≥ 120
Resistivity	ρ	Ωm				0.15
Density	d	g/cm^3				4.90

Remark: Best impedance, and permeability v. s. frequency performance for 10,000 μ_i materials.

Note: Material characteristics are typical for a toroid core.

Product specification will differ from these data due to the influence of geometry and size.

